

## Nimetön

The corresponding steps: clear --- choose work --- learning remote control --- matching success

1, clear: press and hold the learning button, the indicator light, 5 seconds after the off, that clear the success. Before the pair of good remote control all deleted.

2, choose work: clear after the operation does not let go, five seconds after the light flashes, let go is to choose the work of interlocking; if the flash and then let go, then the choice of self-locking work; Three and then let go, then choose to choose the way of working.

3, supporting the remote control: choose a good way to work after the release, and then hold the learning button and hold, light, release the hand, according to the matching remote control to send the signal, the indicator light off, the corresponding remote control pairing success. Repeat the above steps with the remote control.

Note: This product can be equipped with fixed code remote control and learning code remote control, remote control of different address code can be up to 20, such as more than 20 first does not work, and so on. Similar to the fixed code remote control, just have to match the remote control can be compiled with the same address code can be equipped with any remote control; if the remote control for learning code, press the third step can be